



ADD CALL FORWARD NO ANSWER TO PHONE WITH VOICEMAIL

New Software Versions


This programming should be performed on a set that has 3 grey keys underneath the display (if you do not have one of these sets, please call for the appropriate programming template)

This programming does not have to be completed using the phone that has the issue; this can be completed from almost any phone on the system

Programming must be done when phone in idle (no calls incoming or on hold)

The handset is to be left in the cradle while programming

Press Feature 985 (Voicemail Master extension # will appear on display – Write this number down for use in step 7 and press Release (Rls )

1. Press **Feature **266344 (CONFIG)**
2. Password: Enter **23646 (ADMIN)**
3. Press **SHOW**
4. Enter **Ext #** to be programmed
5. Press **SHOW**
6. Press **NEXT**
7. Press **SHOW** twice
8. Press **CHNG**
9. Enter **(Voicemail master extension # from step 1)**
10. Press **NEXT**
11. Enter **# of Rings**
12. Press **NEXT**
13. Press Release (**Rls )**